

Warnings

Always make sure the luminaire is detached from the mains socket  
Always make sure the DC cable is detached from the power supply  
Staring at the operating light source may cause eye injury

| # | Disassemble/dismantle steps                                                                             | Tools needed                           |
|---|---------------------------------------------------------------------------------------------------------|----------------------------------------|
| a | Remove the deco plate (1) by turning it counterclockwise.                                               | -                                      |
| b | Remove cap (2)                                                                                          | -                                      |
| c | Remove the diffuser (3).                                                                                | -                                      |
| d | Remove the reflector (4)                                                                                | -                                      |
| e | Remove flat cable from the LIGHT SOURCE - LED STRIP [9] and LIGHT SOURCE - HUE CONNECT [6]              | -                                      |
| f | Remove low voltage wires of LIGHT SOURCE - HUE CONNECT (6)                                              | LATHEAD SCREWDRIVER OR WAGO TOOL #2065 |
| g | Remove the CONTROL GEAR – PSU (8) from the base (13) by unscrewing screws (7).                          | TORXHEAD SCREW DRIVER T10              |
| h | Remove the LIGHT SOURCE - HUE CONNECT (6) from the base (13) by unscrewing screws (5)                   | TORXHEAD SCREW DRIVER T10              |
| i | Remove HEAT SINK (12) by unscrewing screws (10).                                                        | CROSSHEAD SCREWDRIVER PZ               |
| j | Remove light strip (9) acc. to instruction: 442295215544_L2 Removal and Test Instruction Flex LED strip | See instruction.                       |

- A specific Wago tool #2065 can be ordered separately for wire insertion and release tool:



| SKU          | Color     | Country |
|--------------|-----------|---------|
| 929003055301 | White     | EU      |
| 929003055501 | BLACK     | EU      |
| 929003055401 | ALUMINIUM | EU      |

| #  | COMPONENT                  | QTY |
|----|----------------------------|-----|
| 1  | DECO PLATE                 | 1   |
| 2  | CAP                        | 1   |
| 3  | DIFFUSER                   | 1   |
| 4  | REFLECTOR                  | 1   |
| 5  | SCREW                      | 2   |
| 6  | LIGHT SOURCE - HUE CONNECT | 1   |
| 7  | SCREW                      | 2   |
| 8  | CONTROL GEAR - PSU         | 1   |
| 9  | LIGHT SOURCE - LED STRIP   | 1   |
| 10 | SCREW                      | 3   |
| 11 | WASHER                     | 3   |
| 12 | HEAT SINK                  | 1   |
| 13 | BASE                       | 1   |

|        |  |                                       |  |               |  |            |            |
|--------|--|---------------------------------------|--|---------------|--|------------|------------|
| STATUS |  | DESCRIPTION                           |  | DESIGN ID     |  | 01         | 2021-07-26 |
|        |  | Still ceiling Disassembly instruction |  |               |  |            |            |
| NAME   |  | He Go                                 |  | LOCAL PART ID |  | SH. 2      | A3-L       |
|        |  | CHECKED                               |  | DATE          |  | 2021-07-26 |            |



