



#	COMPONENT	QTY
1	TOP COVER	1
2	SCREW	2
3	PLATE	1
4	CONTROL GEAR - PSU	1
5	SCREW	2
6	LIGHT SOURCE - LED MODULE	1
7	SCREW	1
8	DIFFUSER	1
9	SCREW	2
10	HEAD	1
11	PROFILE	1
12	SCREW	4
13	SCREW	1
14	COVER	1
15	SCREW	1
16	TERMINAL BLOCK	1
17	BASE	1
18	SCREW	4

Warnings

Always make sure the luminaire is detached from the mains socket
 Always make sure the DC cable is detached from the power supply
 Staring at the operating light source may cause eye injury

#	Disassemble/dismantle steps	Tools needed
a	REMOVE THE TOP COVER (1)	FLAT HEAD SCREW DRIVER
b	REMOVE BASE (17) FROM THE PROFILE (11) BY UNSCREWING THE SCREWS (18)	CROSS HEAD SCREW DRIVER
c	REMOVE COVER (14) BY UNSCREWING THE SCREW (13)	CROSS HEAD SCREW DRIVER
d	REMOVE WIRES OF THE CONTROL GEAR - PSU (4) FROM THE TERMINAL BLOCK (16)	FLAT HEAD SCREW DRIVER
e	REMOVE DIFFUSER (8) BY UNSCREWING THE SCREWS (9)	CROSS HEAD SCREW DRIVER
f	REMOVE LIGHT SOURCE - LED MODULE (6) FROM THE PLATE (3) BY UNSCREWING THE SCREW (7)	CROSS HEAD SCREW DRIVER
g	REMOVE WIRES OF THE CONTROL GEAR - PSU (4) FROM THE LIGHT SOURCE - LED MODULE (6)	SOLDER IRON
h	REMOVE THE CONTROL GEAR - PSU (4) BY UNSCREWING THE SCREWS (5)	CROSS HEAD SCREW DRIVER

SKU	Color	Country
915005378101	BLACK	EU
915005378201	BLACK	EU

STATUS	DESCRIPTION	DESIGN ID
2021-04-12	Parterre pedestal black 1x8W 230V Parterre post black 1x8W 230V	DOC 12NC
NAME WH	LOCAL PART ID	SH. 1
CHECKED	DATE	SH. A3-P