



**Warnings**  
Always make sure the luminaire is detached from the mains socket  
Always make sure the DC cable is detached from the power supply  
Staring at the operating light source may cause eye injury

#	Disassembly Instruction	Tools needed
a	Unscrew the Screws [1]. Pull the tube [2] out of the base [3] and unplug the flat wire from the light source.	Screwdriver T6
b	Pull the diffuser [4] out of the tube [2] and remove the light source* [5]	-
c	Unscrew the 3 screws [6] and remove the foot [7] from the base [3]	Screwdriver T20
d	Unscrew [10] the Hue Connect [8] and Control gear [9]. Loosen the wires from the Hue Connect	Screwdriver T10 / Wago Tool #2065
e	Loosen the wires from the cordset [11] and the Control gear [9]. Pull the cordset out of the frame [12] and foot [7]	-

#	COMPONENT	QTY	SKU	Color	Country
1	Screws	2	915005987101	White	EU
2	Tube	1	915005987201	Black	EU
3	Base	1	915005987501	White	NAM
4	Diffuser	1	915005987601	Black	NAM
5	Light Source	1	915005987701	White	UK
6	Screws	3	915005987801	Black	UK
7	Foot	1	929003103601	Black	AUNZ
8	Hue Connect	1	929003479701	Oak	EU
9	Control gear	1	929003516101	Oak	UK
10	Screws	2	929003479901	Oak	NAM
11	Cordset	1			
12	Frame	1			

\*  
FOR LIGHT SOURCE-LED STRIP REMOVAL PLEASE SEE DOCUMENT  
"200604 - Instruction LED Strip Removal Procedure"

GENERAL REQUIREMENTS		TOLERANCES UNLESS OTHERWISE STATED		DIMENSIONS CRITICAL TO PART QUALITY ARE INDICATED BY AN OBLIQUE AROUND A DIMENSION AND A PREFIX THAT IS INDICATING THE DEGREE OF CRITICALITY	
ISO1302 ISO12085	DIMENSION ± mm	ANGLE ± °	ISO 1101/5459	SC (C) OR (CC) (C)	TC (C) OR (CC) (C)
SCALE	UNIT	MATERIAL	TREATMENT	ORDER NO.	QUANT
1:1	MM				
STATUS	DESCRIPTION	DESIGN ID	DATE	SH.	SH.
	Gradient Floor	442295217682	2020-03-19	1	511
NAME	CHECKED	LOCAL PART ID	DATE	SH.	SH.
		442295217682	2020-03-19	1	511
PROPERTY OF: © 2020 Signify Holding					A1-P