



#	COMPONENT	QTY
1	HEAD	1
2	SCREW	1
3	LIGHT SOURCE - LED MODULE	1
4	SCREW	2
5	CONTROL GEAR - PSU	1
6	SCREW	2
7	CLAMPER	1
8	BOX	1
9	PROFILE	1
10	SCREW	4
11	SCREW	1
12	COVER	1
13	SCREW	2
14	SCREW	1
15	TERMINAL BLOCK	1
16	BASE	1

Warnings

Always make sure the luminaire is detached from the mains socket
 Always make sure the DC cable is detached from the power supply
 Staring at the operating light source may cause eye injury

#	Disassemble/dismantle steps	Tools needed
a	PULL OUT THE BASE (16) BY UNSCREWING THE SCREWS (10)	CROSS HEAD SCREW DRIVER
b	REMOVE COVER (12) BY UNSCREWING THE SCREW (11)	CROSS HEAD SCREW DRIVER
c	REMOVE WIRES OF THE CONTROL GEAR - PSU (5) FROM THE TERMINAL BLOCK (15) BY UNSCREWING WIRES FROM THE TERMINAL BLOCK (15)	FLAT HEAD SCREW DRIVER
d	REMOVE THE TERMINAL BLOCK (15) BY UNSCREWING THE SCREW (14)	CROSS HEAD SCREW DRIVER
e	REMOVE PROFILE (9) BY UNSCREWING THE SCREWS (13)	CROSS HEAD SCREW DRIVER
f	REMOVE HEAD (1) FROM THE BOX (8)	FLAT HEAD SCREW DRIVER
g	REMOVE LIGHT SOURCE - LED MODULE (3) BY UNSCREWING THE SCREW (2)	CROSS HEAD SCREW DRIVER
h	REMOVE WIRES OF THE CONTROL GEAR - PSU (5) FROM THE LIGHT SOURCE - LED MODULE (3)	SOLDER IRON
i	REMOVE CLAMPER (7) BY UNSCREWING THE SCREWS (6)	CROSS HEAD SCREW DRIVER
j	REMOVE THE CONTROL GEAR - PSU (5) BY UNSCREWING THE SCREWS (4)	CROSS HEAD SCREW DRIVER

SKU	Color	Country
915005194002	DARK GREY	EU
915005194102	DARK GREY	EU
915005194001	DARK GREY	EU
915005194101	DARK GREY	EU

STATUS	DESCRIPTION	DESIGN ID
2021-04-12	Arbour 4000K pedestal anthracite 1x6W Arbour 4000K post anthracite 1x6W 230V Arbour pedestal anthracite 1x6W 230V Arbour post anthracite 1x6W 230V	DOC 12NC
NAME WH	LOCAL PART ID	SH. 1
CHECKED	DATE	SH. A3-P