



PHILIPS

Compatibility List Professional Q3 2025

Philips CorePro LED PLC/PLL/PLT

Table of contents

Philips CorePro LED PLC

Philips CorePro LED PLC 5.5W 4P G24q-1	2
Philips CorePro LED PLC 6.5W 4P G24q-2	3
Philips CorePro LED PLC 9.5W 4P G24q-3	5

Philips CorePro LED PLL

Philips CorePro LED PLL HF/Mains 8W 4P 2G11	7
Philips CorePro LED PLL HF/Mains 12W 4P 2G11	9
Philips CorePro LED PLL HF/Mains 16.5W 4P 2G11	11
Philips CorePro LED PLL HF/Mains 24W 4P 2G11	13

Philips CorePro LED PLT

Philips CorePro LED PLT HF/Mains 6.5W 4P GX24Q-2	14
Philips CorePro LED PLT HF/Mains 9W 4P GX24Q-3	15
Philips CorePro LED PLT HF/Mains 13.5W 4P GX24Q-3	17
Philips CorePro LED PLT HF/Mains 16W 4P GX24Q-4	18

# Philips CorePro LED PLC 5.5W 4P G24q-1

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
	Ballast is not compatible.	

				Philips CorePro LED PLC 5.5W 4P G24q-1
				Model number / EOC code: 9290037576 / 872016929041900 9290037577 / 872016929043300
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-M 113 TL/PLS/PLC SH	9137004137	1	
	HF-M 113 TL/PLS/PLC LH	9137004139	1	
	BLUE 114 LH TL/PLS/PLC	9137004217	1	
	RED 114 SH TL/TL5/PL-C/S	9137004232	1	
	HF-P 1 13-17 PL-T/C/R EII	9137006311	1	
	HF-P 2 13-17 PL-T/C/R EII	9137006312	2	
	EB-C 113 PL-T/C 220	9137131984	1	
	EB-C 213 PL-T/C 220	9137131985	2	
	HF-M 114 TL/PLS/PLC LH	9137004170	1	
	BLUE 124 SH TL/TL5/PLL	9137004179	1	
	HF-P 113 PL-C 220-240	9137001298	1	
OSRAM	QT-ECO 1X4-16/220-240 L		1	
	QT-ECO 1X4-16/220-240 S		1	*
	QTP-D/E 1X10-13		1	
	QTP-D/E 2X10-13		2	
	QT-ECO 2X5-11/220-240 S		2	
VOSSLOH-SCHWABE	ELXc 213.870	188698	2	
	ELXc 213.870	188698	1	*
	ELXs 121.901	188663	1	**
	ELXs 121.904	188663	1	***
TRIDONIC ATCO	PCA 1x11/13 TC EXCEL one4all	22185134	1	
	PCA 1x11/13 TC ECO	22185126	1	
	PCA 2x11/13 TC EXCEL one4all	22185135	2	
	PCA 2x11/13 TC ECO	22185127	2	
	PC 1x5-16W BASIC	24138830	1	**
	PC 1x5-16W BASIC sl	24138833	1	**
	PC 1/2x9-13 TC PRO	22176405	1	
	PC 1/2x9-13 TC PRO	22176405	2	
BAG HUECO	BCD13.1-2Q-01/220-240/1-10V	10096393	2	*
	BCD13.1-2Q-01/220-240/1-10V	10096393	1	**
	BCS21.1-2LS-01/220-240	10095043	2	*
	BCS21.1-2LS-01/220-240	10095043	1	*
	BCS21.1-2QI-01/220-240	10095743	2	*
	BCS21.1-2QI-01/220-240	10095743	1	*
	EBS21.1C-01/220-240	10050990	1	*
	EBS21.1M-01/220-240	10050994	1	**
	EBS16.1C-01/220-240	10050989	1	*
TCI	BCC 121	137946HTC	1	*
	BCC 121/2	137969/21MM	1	**
	BCC 121/2 SL	137944/21H	1	**
	BCC 121 SL	137944B/21H	1	*
	BCC 121 IP54	137969IP21MM	1	*
	MBQ 113/2	137968/113	1	
	MB213	137988/213	2	**
	MB213/2	137988/2132	2	**
	MBQ 213/2	137968/213	2	
	BCC 116	137945HTC	1	**
Others	Direct mains 220-240 ACV			

### Philips CorePro LED PLC

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLC 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLC 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLC 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLC 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLC 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLC 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.



# Philips CorePro LED PLC 6.5W 4P G24q-2

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
	Ballast is not compatible.	

				Philips CorePro LED PLC 6.5W 4P G24q-2
				Model number / EOC code: 9290037578 / 872016929045700 9290037579 / 872016929047100
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-P 118 PL-T/C III	9137006485	1	
	HF-P 1/218 PL-T/C III	9137006486	1	
	HF-P 218 PL-T/C III 220-240V 50/60Hz	9137006486	2	
	HF-M RED 118 SH PLC/PL-T 230-240V	9137004234	1	**
	HF-S 218 PL-T/C II SR	9137130358	2	
	HF-S 1/218 PL-T/C II SR 220-240V 50/60Hz	9137130358	1	
	HF-S 118 PL-T/C II SR 220-240V 50/60Hz	9137130359	1	
	HF-P 218 PL-T/C 220-240	9137001553	2	
	HF-P 118 PL-T/C EII	9137006309	1	
	HF-P 218 PL-T/C EII	9137006310	2	
	EB-C 118 PL-T/C 220-240	9137131986	1	
	EB-C 218 PL-T/C 220	9137131987	2	
	HF-R 218 PL-T/C EII	9137006801	2	
	HF-R 118 PL-T/C EII	9137006800	1	
	HF-R TD 218 PL-T/C EII 220-240V 50/60Hz	9137006259	2	
	HF-R TD 118 PL-T/C EII 220-240V 50/60Hz	9137006260	1	
	HF-R 118 PL-T/C 220-240	9137001260	1	
	HF-P 1/218 PL-T/C III	9137006486	2	
	HF-P 118 PL-T/C 220-240	9137001104	1	
	HF-R 218 PL-T/C 220-240	9137006050	2	
	EB-S 218 PLT/C 220-240	9137100653	2	
	HF-S 1/218 PL-T II SR 220-240V 50/60Hz	9137130358	2	
OSRAM	QTP-T/E 1X18, 2X18	A72031900DG	1	
	QTP-T/E 1X18, 2X18	A72031900DG	2	
	QT-ECO T/E 2X18/220-240	A72924F00DG	2	
	QTP-T/E 2x18	A57063200DG	2	
	QT-D/E 1x18/230-240		1	
	EZ-T/E 1x18/220-240	AA403390155	1	
	EZ-T/E 2x18/220-240	AA403450155	2	
	OT-ECO 1X18-21 /220-240s	A4896310255	2	
	Qti-T/E 2x18-42 DIM	AA39453 05BS	1	
HELVAR	EL1/2x18TCs		1	
	EL1/2x18TCs		2	
	EL1/2x18-42TCs		1	
	EL1/2x18-42TCs		2	
TRIDONIC ATCO	PC 1/2x18 TC PRO sr	22176416	1	*
	PC 1/2x18 TC PRO sr	22176416	2	*
	PC 1x18 TC TOP	28000073	1	
	PC 2x18 TC TOP	28000074	2	
	PC 1/2x18 TC PRO	22176407	1	*
	PC 1/2x18 TC PRO	22176407	2	*
	PC PRO 18 FSQ b101	22082606	1	**
	PC 1X18-24W BASIC sl	22176000	1	
	PC 2X18 TC TOP sr	28000078	2	
BAG HUECO	BCS18.1-2Q-01 / 220-240	10097544	1	*
	BCS18.1-2Q-01 / 220-240	10097544	2	
	BCS18.1-2LS-01 / 220-240	10095044	1	**
	BCS18.1-2LS-01 / 220-240	10095044	2	*

# Philips CorePro LED PLC 6.5W 4P G24q-2

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
	Ballast is not compatible.	

				Philips CorePro LED PLC 6.5W 4P G24q-2
				Model number / EOC code: 9290037578 / 872016929045700 9290037579 / 872016929047100
				AC (50 Hz) on HF Ballast Compatible
VOSSLOH - SCHWABE	Ballast type	10nc	Lamps on ballast	
	ELXs 121.901	188663	1	
	ELXS 121.904	188664	1	
	ELXC 218.871	188699	1	**
	ELXC 218.871	188699	2	*
	ELXC 142.872	188700	1	
	ELXC 142.872	188700	2	
	ELXc 242.837	188643	1	
TCI	MBQ 118/2	137968/118	1	
	MBQ 218/2	137968/218	2	
	BCC 121	137946HTC	1	
ELT	BE 218-TC-5	NA	1	
	BE 218-TC-5	NA	2	
Others	Direct mains 220-240 ACV			

### Philips CorePro LED PLC

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLC 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLC 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLC 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLC 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLC 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLC 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

# Philips CorePro LED PLC 9.5W 4P G24q-3

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				Philips CorePro LED PLC 9.5W 4P G24q-3
				Model number / EOC code: 9290037580 / 872016929049500 9290037581 / 872016929051800
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	*
	HF-P 226 PL-T/C III	9137006488	1	*
	HF-P 126 PL-T/C III	9137006487	1	
	HF-P 122-42 PL-T/C/L/T5C EII	9137006307	2	
	HF-P 2 22-42 PL-T/C/L/TL5C EII	9137006308	1	(1)
	HF-S 226 PL-T/C II SR	9137130356	2	
	HF-S 226 PL-T/C/L/TL5C II SR	9137130356	1	
	HF-S 126 PL-T/C/L/TL5C II SR	9137130357	1	
	HF-P 2 26-42 PL-T/C 220-240	9137001950	2	
	EB-C 126 PL-T/C 220-240V 50/60Hz	9137131988	1	
	EB-C 226 PL-T/C 220	9137131989	2	
	HF-P 1/226 PL-T/C III 220-240V 50/60Hz	9137006488	1	
	HF-P 1/226 PL-T/C III 220-240V 50/60Hz	9137006488	2	
	HF-S 1/2 26 PL-T/C II SR 220-240V 50/60Hz	9137130356	2	
	HF-S 1/2 26 PL-T/C II SR 220-240V 50/60Hz	9137130356	1	
	HF-R 126-42 PL-T/C EII	9137006266	2	
	HF-Ri TD 2 26-42 PL-T/C E+	9137006848	1	
	HF-Ri TD 126-42 PL-T/C E+	9137006847	1	
	HF-R TD 126-42 PL-T/C EII 220-240	9137006258	2	
	HF-P 126 PL-T/C 220-240	9137001100	1	
HFP 226	4411347303 31	2		
EB-P 126 PLT/C ICC 220-240V 50/60Hz	9137100654	2	*	
HF-P 1 26-42 PL-T/C	9137001932	2		
OSRAM	QTP-M 1X26-42	A6979600455	1	
	QTP-M 2x26-32	A6979950455 69799500DG	2	
	QTP-M 2x26-32	A6979950455 A69799500DG	1	
	QT-M 2x26-42/220-240 S	A526/5500DG	2	
	QTP-T/E 1X26-42,2X26	A72032500DG	2	
	QTP-T/E 1x26-42, 2x26	A72032500DG	1	
	QT-ECO T/E 2X26/220-240	A53702300DG	2	
	QT-ECO 1X26/220...240 S	A48946102DG	1	
	QT-T/E 2x26/230-240		2	
	QT-M 1x26-42/220-240 S	A48989E00DG	1	
	EZ-T/E 1X26/220-240	AA403410155	1	
	Qti-T/E 2x18-42 DIM	AA39453 05B5	2	
	QT DALI-T/E 2x26-42/230-240 DIM		2	
	EZ-T/E 2x26/220-240	AA403470155	2	
VOSSLOH- SCHWABE	ELXC 142.872	188700	2	(1)
	ELXC 142.872	188700	1	
	ELXC 242.837	188643	2	(1)
	ELXs 126.906	188667	1	
	CBC-226142	540426	2	
	ELXC 142.876	188888	1	
	ELXC 142.876	188888	2	(1)
	ELXc 242.877	188889	2	(1)

# Philips CorePro LED PLC 9.5W 4P G24q-3

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				Philips CorePro LED PLC 9.5W 4P G24q-3
				Model number / EOC code: 9290037580 / 872016929049500 9290037581 / 872016929051800
				AC (50 Hz) on HF Ballast Compatible
TRIDONIC ATCO	Ballast type	10nc	Lamps on ballast	*
	PC1/2x26 TC PRO sr	22176417	1	**
	PC1/2x26 TC PRO sr	22176417	2	*
	PC 1/2 x 26-42 TC PRO PC 1/2 x 26-42 TC PRO	22176408	1	*
	PC 2x26-42 TC PRO	22176408	2	
	PC 1x26-42 TC TOP	22176410	2	
	PC 2x26 TC TOP	28000075	1	(1)
	PC 2x26 TC TOP	28000076	2	
BAG HUECO	BCS42.1/26.2LS-01/220-240	10095045	1	
	BCS42.1/26.2LS-01/220-240	10095045	2	
	BCS42.1/26.2QI-01/220-240	10095745	1	
	BCS42.1/26.2QI-01/220-240	10095745	2	
	BCS70.1/42.2Q-01/220-240	10097546	1	
	BCS70.1/42.2Q-01/220-240	10097546	2	
	BCS42.1Q-01/220-240	10097535	1	
	BCD57.1/32.2Q-01/220-240/DALI	10096397	1	
	BCD57.1/32.2Q-01/220-240/DALI	10096397	2	
	BCS42.1/26.2Q-01/220-240	10097545	1	
HELVAR	EL1/2x18-42TCs		1	
	EL1/2x18-42TCs		2	
	EL2X32/42TCS		1	*
TCI	MBQ 226/2	137968/226	2	
	MBQ 142/2	137968/142	1	** (1)
	MBQ 242/2	137962/242	1	** (1)
	MBQ 242/2	137962/242	2	
	BCC 126.	137949HTC	1	
	MB226/2	137989Tc	2	(1)
HUCO	EVG-HP 1x/2x 15-42W HC	22176		
	EVG-HP 1x/2x 15-42W HC	22176		
OTHER				
	Direct mains 220-240 ACV			

### Philips CorePro LED PLC

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLC 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLC 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLC 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLC 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLC 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLC 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

# Philips CorePro LED PLL HF/Mains 8W 4P 2G11

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLL HF/Mains 8W 4P 2G11
				Model number / EOC code: 9290042674 / 872110305087800 9290042675 / 872110305089200
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-Performer 1 22-42 PL-T/C/L/TL5C EII 220-240V	9137006307	1	
	HF-Performer 2 22-42 PL-T/C/L/TL5C EII 220-240V	9137006308	2	
	HF-Pi 1 14/21/24/39 TL5 EII 220-240	9137006240	1	
	HF-Pi 2 14/21/24/39 TL5 EII 220-240	9137006242	2	
	HF-Pi 3/4 14/24 TL5/PLL EII	9137006576	4	
	HF-Pi 3/4 14/24 TL5/PLL EII	9137006576	3	
	HF-MATCHBOX BLUE 124 LH TL/TL5/PLL	9137004180	1	
	HF-MATCHBOX BLUE 124 SH TL/TL5/PLL	9137004179	1	
	HF-MATCHBOX RED 124 SH TL/TL5/PLL	9137004206	1	
	HF-P 1 18-24 PL-L	9137001931	1	
	EB-S 1 24 TL/PL SH	9137100283	1	
OSRAM	QT-ECO 1x18-24/220-240 S		1	
	QT-FIT8 1x18		1	*
	QT-M 1x26-42/230-240 S		1	
	QTP-M 1X26-42		1	
	QTP-M 2X26-32		2	
	QTP-OPTIMAL 1x18-40		1	
	QTP-OPTIMAL 2x18-40		2	*
HELVAR	EL1x36/40/18s		1	*
	EL1/2x18-42TCs	4219001K47206984	2	
	EL1/2x18-42TCs	4219001K47206984	1	
	EL1/2x18-42TCs	4219001Q09604620	1	
	EL1/2x18-42TCs	4219001Q09604620	2	
VOSSLOH	ELXc 142.872	188700	2	
	ELXc 142.872	188700	1	*
	ELXc 142.876	188888	2	
	ELXc 142.876	188888	1	*
	ELXc 242.837	188643	2	
	ELXc 242.877	188889	2	
TRIDONIC	PC 1/2x26-42 TC PRO	22176408	2	*
	PC 1/2x26-42 TC PRO	22176408	1	*
	PC 1x18-24W BASIC sl	22176000	1	
	PC 2x26-42 TC PRO	22176410	2	*
	PC 2/14-21/24/39 T5 PRO-M Ip	22176185	2	
	PC 1/14-35/24/39 T5 PRO-M Ip	22176182	1	
	PC 2x36/4x18 T8 TEC	87500260	4	
BAG-HUECO	BCS39.1FX-11/220-240	10077581	1	*
	BCS39.2FX-11/220-240	10077582	2	
	BCS42.1/26.2LS-01/220-240	10095045	2	
	BCS42.1/26.2LS-01/220-240	10095045	1	*
	BCS42.1/26.2Q-01/220-240	10097545	2	
	BCS42.1/26.2Q-01/220-240	10097545	1	
	BCS42.1/26.2QI-01/220-240	10095745	2	
	BCS42.1/26.2QI-01/220-240	10095745	1	*
	BCS42.1Q-01/220-240	10097535	1	
	MLS14/24.3-4.FR-11/220-240	10095345	4	*
	MLS14/24.3-4.FR-11/220-240	10095345	3	
	MLS39.1-2FR-11/220-240	10092026	2	**
	MLS39.1-2FR-11/220-240	10092026	1	**
	BCD57.1/32.2Q-01/220-240/DALI	10096397	1	*
	BCD57.1/32.2Q-01/220-240/DALI	10096397	2	*

# Philips CorePro LED PLL HF/Mains 8W 4P 2G11

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLL HF/Mains 8W 4P 2G11
				Model number / EOC code: 9290042674 / 872110305087800 9290042675 / 872110305089200
				AC (50 Hz) on HF Ballast Compatible
TCI	Ballast type	10nc	Lamps on ballast	** (1)
				** (1)
				** (1)
				*
				*
HUCO	EVG-HP 1x/2x 15-42W HC	097545	2	
	EVG-HP 1x/2x 15-42W HC	097545	1	
OTHER	Direct mains			
	Electro Magnetic Ballast			

### Philips CorePro LED PLL

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLL 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLL 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLL 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLL 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLL 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLL 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.



# Philips CorePro LED PLL HF/Mains 12W 4P 2G11

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
	Ballast is not compatible.	

				CorePro LED PLL HF/Mains 12W 4P 2G11
				Model number / EOC code: 9290042676 / 872110305091500 9290042677 / 872110305093900
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-Performer 1 22-42 PL-T/C/L/TL5C EII 220-240V	9137006307	1	
	HF-Performer 2 22-42 PL-T/C/L/TL5C EII 220-240V	9137006308	2	
	HF-Pi 1 14/21/24/39 TL5 EII 220-240	9137006240	1	*
	HF-Pi 2 14/21/24/39 TL5 EII 220-240	9137006242	2	*
	HF-Pi 3/4 14/24 TL5/PLL EII	9137006576	4	
	HF-Pi 3/4 14/24 TL5/PLL EII	9137006576	3	
	HF-MATCHBOX BLUE 124 LH TL/TL5/PLL	9137004180	1	
	HF-MATCHBOX BLUE 124 SH TL/TL5/PLL	9137004179	1	
	HF-MATCHBOX RED 124 SH TL/TL5/PLL	9137004206	1	
	HF-P 1 18-24 PL-L	9137001931	1	
	EB-S 1 24 TL/PL SH	9137100283	1	
	HF-Ri TD 2 14/21/24/39 TL5 E+	9137006984	2	
OSRAM	QT-ECO 1x18-24/220-240 S		1	
	QT-M 1x26-42/230-240 S		1	
	QT-M 2x26-42/220-240 S		2	
	QTP-M 1X26-42		1	
	QTP-M 2X26-32		2	
	QT-T/E 2x26/230-240		2	
	QTP-OPTIMAL 1x18-40		1	
	QTP-OPTIMAL 2x18-40		2	
HELVAR	EL1/2x18-42TCs	4219001K47206984	2	
	EL1/2x18-42TCs	4219001K47206984	1	
	EL1/2x18-42TCs	4219001Q09604620	1	
	EL1/2x18-42TCs	4219001Q09604620	2	
VOSSLOH	ELXc 142.872	188700	2	
	ELXc 142.872	188700	1	*
	ELXc 142.876	188888	2	
	ELXc 142.876	188888	1	*
	ELXc 242.837	188643	2	
	ELXc 242.877	188889	2	
	ELXc 128.869	188589	1	*
	ELXc 126.906	188667	1	
TRIDONIC	PC 1/2x26-42 TC PRO	22176408	2	**
	PC 1/2x26-42 TC PRO	22176408	1	**
	PC 1/2x26-42 TC PRO sr	22176417	1	**
	PC 1/2x26-42 TC PRO sr	22176417	2	**
	PC 1x18-24W BASIC sI	22176000	1	
	PC 2x26-42 TC PRO	22176410	2	**
	PC 2/14-21/24/39 T5 PRO-M Ip	22176185	2	
	PC 1/14-35/24/39 T5 PRO-M Ip	22176182	1	

# Philips CorePro LED PLL HF/Mains 12W 4P 2G11

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLL HF/Mains 12W 4P 2G11
				Model number / EOC code: 9290042676 / 872110305091500 9290042677 / 872110305093900
				AC (50 Hz) on HF Ballast Compatible
BAG-HUECO	Ballast type	10nc	Lamps on ballast	*
	BCS39.1FX-11/220-240	10077581	1	
	BCS39.2FX-11/220-240	10077582	2	
	BCS42.1/26.2LS-01/220-240	10095045	2	
	BCS42.1/26.2LS-01/220-240	10095045	1	*
	BCS42.1/26.2Q-01/220-240	10097545	2	
	BCS42.1/26.2Q-01/220-240	10097545	1	
	BCS42.1/26.2QI-01/220-240	10095745	2	
	BCS42.1/26.2QI-01/220-240	10095745	1	
	BCS42.1Q-01/220-240	10097535	1	
	MLS14/24.3-4.FR-11/220-240	10095345	4	
	MLS14/24.3-4.FR-11/220-240	10095345	3	
	MLS39.1-2FR-11/220-240	10092026	2	
	MLS39.1-2FR-11/220-240	10092026	1	*
	BCD57.1/32.2Q-01/220-240/DALI	10096397	1	*
	BCD57.1/32.2Q-01/220-240/DALI	10096397	2	**
TCI	BCC 124	137947HTC	1	*(1)
	BCC 124/2	137969/24MM	1	** (1)
	BCC 124/2 SL	137944H	1	*(1)
	MBQ 224/2	137968/224	2	
	MB 226/2	137989TC	2	
	BCC 126	137949HTC	1	
HUCO	EVG-HP 1x/2x 15-42W HC	097545	2	
	EVG-HP 1x/2x 15-42W HC	097545	1	
OTHERS	Direct mains			
	Electro Magnetic Ballast			

### Philips CorePro LED PLL

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLL 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLL 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLL 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLL 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLL 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLL 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

# Philips CorePro LED PLL HF/Mains 16.5W 4P 2G11

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
	Ballast is not compatible.	

				CorePro LED PLL HF/Mains 16.5W 4P 2G11
				Model number / EOC code: 9290042678 / 872110305095300 9290042679 / 872110305097700
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-P 136 TL-D III 220-240V 50/60Hz IDC	9137130315	1	
	HF-P 236 TL-D III 220-240V 50/60Hz IDC	9137130316	2	
	HF-P 118/136 TL-D III 220-240V 50/60Hz	9137130315	1	
	HF-P 218/236 TL-D III 220-240V 50/60Hz	9137130316	2	
	HF-S 136 TL-D II 220-240V 50/60Hz	9137130321	1	
	HF-S 236 TL-D II 220-240V 50/60Hz	9137130324	2	
	HF-S 218/236 TL-D II 220-240V 50/60Hz	9137130324	2	
	HF-E 136 TL-D II 220-240 50/60Hz	9137130410	1	
	HF-E 236 TL-D II 220-240 50/60Hz	9137130411	2	
	HF-S 336 TL-D II 220-240V 50/60Hz	9137130327	3	
	HF-Pi 1 14/21/24/39 TL5 EII 220-240V	9137006240	1	*
	HF-Pi 2 14/21/24/39 TL5 EII 220-240V	9137006242	2	**
	HF-P 236 PLL EII 220-240V 50/60Hz	9137001923	2	
	HF-P 236 PL-L III IDC 220-240V 50/60Hz	9137130285	2	
	HF-P 136 PLL 220-240	9137001145	1	
	HF-R 136 TL-D EII 220-240V 50/60Hz	9137006092	1	
	HF-R 236 TL-D EII 220-240V 50/60Hz	9137006093	2	
	HF-Regulator 236 PLL EII 220-240V 50/60Hz	9137006200	2	**
	HF-R 136 PLL 220-240	9137001156	1	*
	HF-R 236 PLL 220-240	9137001157	2	*
	HF-Ri TD I 14/21/24/39 TL5 E+	9137006983	1	**
	HF-Ri TD 2 14/21/24/39 TL5 E+	9137006984	2	**
	HF-B 136 TLD 220-240	9137001122	1	*
	HF-B 136 TLD EII 220-240	9137001926	1	**
	HF-B 236 TLD EII 220-240	9137001928	2	
OSRAM	Qti 1x14/24/21/39 GII		1	
	Qti 2x14/24/21/39 GII		2	
	QT-M 2x26-42/220-240 S	A52675500DG	2	*
	QTP-DL 1x36-40		1	*
	QTP-DL 2x36-40		2	**
	QTP-M 1x26-42	A6979600455	1	
	QTP-M 2x26-32	A6979950455 A69799500DG	2	*
	QTP-OPTIMAL 1x18-40	AA5095703DG		
	QTP-OPTIMAL 2x18-40	AA517320755	2	**
	QT-M 1x26-42/230-240 S	A48989E00DG	1	*
HELVAR	EL1x39/36ngn5		1	
	EL2x39/36ngn5		2	
	EL2x39/36s		2	**
	EL1/2x36/38TCs - Single		1	
	EL1/2x36/38TCs - dual		2	
VOSSLOH	ELXc 140.862	188140	1	
	ELXc 240.863	188616	2	*
	ELXc 142.872	188700	1	
	ELXc 242.837	188643	2	
	ELXc 236.208	188705	2	*
	ELXc 142.876	188888	1	
	ELXc 242.877	188889	2	*

# Philips CorePro LED PLL HF/Mains 16.5W 4P 2G11

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
	Ballast is not compatible.	

				CorePro LED PLL HF/Mains 16.5W 4P 2G11
				Model number / EOC code: 9290042678 / 872110305095300 9290042679 / 872110305097700
				AC (50 Hz) on HF Ballast Compatible
TRIDONIC	Ballast type	10nc	Lamps on ballast	*
	PC 1/36 TCL PRO	87500507	1	**
	PC 2/36 TCL PRO	87500518	2	**
	PC 3/36 T8 PRO	22176231	3	
	PC 1/14-35/24/39 T5 PRO-M Ip	22176182	1	*
	PC 2/14-21/24/39 T5 PRO-M Ip	22176185	2	**
	PC 2x36/4x18 T8 TEC	87500260	2	
BAG-HUECO				
	BCS38.1Q-01/220-240	10097437	1	
	BCS39.1FX-11/220-240	10077581	1	
	BCS42.1Q-01/220-240	10097535	1	
	MLS39.1-2FR-11/220-240 - Single	10092026	1	**
	MLS39.1-2FR-11/220-240 - dual	10092026	2	**
	BCS39.2FX-11/220-240	10077582	2	
Trilux	D58.1-23021 E	166072	1	**
OTHERS	Direct mains			
	Electro Magnetic Ballast			

### Philips CorePro LED PLL

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLL 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLL 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLL 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLL 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLL 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLL 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

# Philips CorePro LED PLL HF/Mains 24W 4P 2G11

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLL HF/Mains 24W 4P 2G11
				Model number / EOC code: 9290042680 / 872110305099100 9290042681 / 872110305101100
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-E 1/2 58 TL-D II 220-240 50/60Hz	9137130409	1	
	HF-E 1/2 58 TL-D II 220-240 50/60Hz	9137130409	2	
	HF-P 158 TL-D III 220-240V 50/60Hz IDC	9137130318	1	
	HF-P 258 TL-D III 220-240V 50/60Hz IDC	9137130319	2	
	HF-P 154/155 TL5 HO/PL-L III IDC	9137130282	1	
	HF-P 254/255 TL5 HO/PL-L III IDC	9137130283	2	
	HF-S 154 TL5 II 220-240V 50/60Hz	9137130336	1	*
	HF-S 254 TL5 II 220-240V 50/60Hz	9137130337	2	
	HF-S 158 TL-D II 220-240V 50/60Hz	9137130322	1	
	HF-S 258 TL-D II 220-240V 50/60Hz	9137130325	2	
	HF-S 258 TL-D II HT 220-240V 50/60Hz	9137006899	2	
	HF-B 158 TLD 220-240	9137001123	1	
	HF-B 158 TLD EII 220-240	9137001927	1	
	HF-B 258 TLD EII 220-240	9137001929	2	
	HF-Pi 1 28/35/49/54 TL5 EII 220-240V	9137006241	1	*
	HF-Pi 2 28/35/49/54 TL5 EII 220-240V	9137006243	2	*
	HF-R 154 TL5 EII 220-240V 50/60Hz	9137006088	1	
	HF-R 254 TL5 EII 220-240V 50/60Hz	9137006089	2	
OSRAM	QT-FQ 2x80		2	** (1)
	Qti 1x35/49/80 GII		1	**
	Qti 2x35/49/80 GII		2	*
	QTP-DL 2x55 GII		2	*
	QTP-DL 1x55 GII		1	
	QTP-OPTIMAL 1x54-58		1	
	QTP-OPTIMAL 2x54-58		2	
HELVAR	EL1x55ngn5		1	
	EL2x55ngn5		2	
	EL1x55s		1	*
	EL2x55s		2	*
VOSSLOH	ELXc 180.866	188144	1	*
	ELXc 254.865	188618	2	
	ELXc 280.538	188619	2	
	ELXc 155.378	188680	1	*
TRIDONIC	PC 1x80 T5 PRO Ip	22185209	1	*
	PC 2x55 TCL PRO Ip	22185286	2	**
	PC 1/55 TCL PRO	22176169	1	
	PC 2/55 TCL PRO	22176233	2	
	PC 1/14-35/49/80 T5 PRO-M Ip	22176184	1	
	PC 1x58 T8 PRO Ip	22185215	1	
	PC 2x58 T8 PRO sI	22185218	2	
	PC 1x58 T8 TEC	87500150	1	**
	PC 2x58 T8 TEC	87500151	2	
	PC 2/58 T8 PRO	22176095	2	
BAG-HUECO	BCS54.1FX-11/220-240	10077585	1	*
	MLS80.1/54.2FR-11/220-240	10071609	1	*
	MLS80.1/54.2FR-11/220-240	10071609	2	
	BCS54.1FR-01/220/240	10075881	1	
	D58.1-23021 E	166072	1	
	D58.2-23021 E	166082	2	*
	BCS58.15R-01/220-240	10051002	1	
Trilux	D58.1-23021 E		1	
TCI	BTLT 254	137999/54	2	
OTHERS	Direct mains			
	Electro Magnetic Ballast			

### Philips CorePro LED PLL

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLL 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLL 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLL 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLL 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLL 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLL 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.



# Philips CorePro LED PLT HF/Mains 6.5W 4P GX24Q-2

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLT HF/Mains 6.5W 4P GX24Q-2
				Model number / EOC code: 9290042666 / 872110304973500 9290042667 / 872110304975900
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	EB-S 218 PLT/C 220-240	9137100653	2	
	HF-P 118 PL-T/C EII	9137006309	1	
	HF-P 118 PL-T/C III	9137006485	1	
	HF-M RED 118 SH PL-C/PL-T	9137004234	1	**
	HF-P 118 PL-T/C 220-240	9137001104	1	
	HF-P 1/218 PL-T/C III	9137006486	1	*
	HF-P 1/218 PL-T/C III	9137006486	2	
	HF-P 218 PL-T/C EII	9137006310	2	
	HF-P 218 PL-T/C III 220-240V 50/60Hz	9137006486	2	
	HF-P 218 PL-T/C 220-240	9137001553	2	
	HF-S 118 PL-T/C II SR 220-240V 50/60Hz	9137130359	1	
	HF-S 218 PL-T/C II SR	9137130358	2	
	HF-S 1/218 PL-T/C II SR 220-240V 50/60Hz	9137130358	1	*
	HF-S 1/218 PL-T/C II SR 220-240V 50/60Hz	9137130358	2	
OSRAM	QTP-T/E 1X18, 2X18	A72031900DG	1	
	QTP-T/E 1X18, 2X18	A72031900DG	2	
	QTP-T/E 2x18	A57063200DG	2	
	QT-D/E 1x18/230-240		1	
	QT-ECO T/E 2X18/220-240	A72924F00DG	2	
TRIDONIC	PC 1x18 TC TOP	28000073	1	
	PC 2x18 TC TOP	28000074	2	
	PC 2X18 TC TOP sr	28000078	2	
	PC 1/2x18 TC PRO	22176407	1	*
	PC 1/2x18 TC PRO	22176407	2	*(1)
	PC 1/2x18 TC PRO sr	22176416	1	*
	PC 1/2x18 TC PRO sr	22176416	2	*
	PC PRO 18 FSQ b101	22082606	1	**
	PC 1X18-24W BASIC sl	22176000	1	
VOSSLOH	ELXs 121.901	188663	1	
	ELXs 121.904	188664	1	
	ELXc 218.871	188699	1	**
	ELXc 218.871	188699	2	*
	ELXc 142.872	188700	1	
	ELXc 142.872	188700	2	
BAG-HUECO	BCS18.1-2LS-01 / 220-240	10095044	1	**
	BCS18.1-2LS-01 / 220-240	10095044	2	*
	BCS18.1-2Q-01 / 220-240	10097544	1	*
	BCS18.1-2Q-01 / 220-240	10097544	2	
TCI	MBQ 118/2	137968/118	1	
	MBQ 218/2	137968/218	2	
	BCC 121	137946HTC	1	
HELVAR	EL1/2x18TCs	4217001P30402078 8	1	
	EL1/2x18TCs	4217001P30402078 8	2	*
ELT	BE 218-TC-5		1	
	BE 218-TC-5		2	
OTHERS	Direct mains			
	Electro Magnetic Ballast			

### Philips CorePro LED PLT

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLT 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLT 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLT 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLT 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLT 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLT 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

# Philips CorePro LED PLT HF/Mains 9W 4P GX24Q-3

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLT HF/Mains 9W 4P GX24Q-3
				Model number / EOC code: 9290042668 / 872110304977300 9290042669 / 872110304979700
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	*
	HF-P 126 PL-T/C III	9137006487	1	
	HF-P 1 22-42 PL-T/C/L/T5C EI	9137006307	1	
	HF-P 1 26-42 PL-T/C	9137001932	1	
	HF-P 1/226 PL-T/C III 220-240V 50/60Hz	9137006488	1	
	HF-P 1/226 PL-T/C III 220-240V 50/60Hz	9137006488	2	
	HF-P 226 PL-T/C III	9137006488	2	*
	HF-P 2 22-42 PL-T/C/L/TL5C EII	9137006308	2	
	HF-P 2 26-42 PL-T/C 220-240	9137001950	2	
	HFP 226 (Philips Luminaires)	441134730331	2	
	HF-S 126 PL-T/C/L/TL5C II SR	9137130357	1	
	HF-S 1/2 26 PL-T/C II SR 220-240V 50/60Hz	9137130356	1	
	HF-S 1/2 26 PL-T/C II SR 220-240V 50/60Hz	9137130356	2	
	HF-S 226 PL-T/C II SR	9137130356	2	
	EB-P 126 PLT/C ICC 220-240V 50/60Hz	9137100654	1	*
OSRAM	QTP-M 1X26-42	A6979600455	1	
	QTP-M 2x26-32	A6979950455 A69799500DG	2	*
	QTP-T/E 1x26-42, 2x26	A72032500DG	1	
	QTP-T/E 1X26-42,2X26	A72032500DG	2	
	QT-ECO 1X26/220...240 S	A48946102DG	1	
	QT-ECO T/E 2X26/220-240	A53702300DG	2	
	QT-M 2x26-42/220-240 S	A5267550355 A52675500DG	2	
	QT-T/E 2x26/230-240		2	
	QT-M 1x26-42/220-240 S	A48989E00DG	1	
TRIDONIC ATCO	PC 1/2x26-42 TC PRO sr	22176417	1	*
	PC 1/2x26-42 TC PRO sr	22176417	2	**
	PC 1/2 x 26-42 TC PRO	22176408	1	*
	PC 1/2 x 26-42 TC PRO	22176408	2	*
	PC 1x26-42 TC TOP	28000075	1	
	PC 2x26 TC TOP	28000076	2	
	PC 2x26-42 TC PRO	22176410	2	*
VOSSLÖH	ELXs 126.906	188667	1	
	CBC-226142	540426	2	
	ELXc 142.872	188700	1	
	ELXc 142.872	188700	2	(1)
	ELXc 142.876	188888	1	
	ELXc 142.876	188888	2	(1)
	ELXc 242.837	188643	2	(1)
	ELXc 242.877	188889	2	
BAG-HUECO	BCS42.1/26.2LS-01/220-240	10095045	1	
	BCS42.1/26.2LS-01/220-240	10095045	2	
	BCS42.1/26.2QI-01/220-240	10095745	1	
	BCS42.1/26.2QI-01/220-240	10095745	2	
	BCS70.1/42.2Q-01/220-240	10097546	1	
	BCS70.1/42.2Q-01/220-240	10097546	2	
	BCS42.1Q-01/220-240	10097535	1	
	BCS42.1/26.2Q-01/220-240	10097545	1	
	BCS42.1/26.2Q-01/220-240	10097545	2	

# Philips CorePro LED PLT HF/Mains 9W 4P GX24Q-3

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLT HF/Mains 9W 4P GX24Q-3
				Model number / EOC code: 9290042668 / 872110304977300 9290042669 / 872110304979700
				AC (50 Hz) on HF Ballast Compatible
TCI	Ballast type	10nc	Lamps on ballast	(1)
	BCC 126.	137949HTC	1	
	MB226/2	137989Tc	2	
	MBQ 226/2	137968/226	2	
	MBQ 142/2	137968/142	1	** (1)
	MBQ 242/2	137962/242	1	** (1)
HELVAR				
	EL1/2x18-42TCs	4219001Q09604620 1	1	*
	EL1/2x18-42TCs	4219001Q09604620 1	2	*
	EL2x32/42TCs	4218001K03102451 9	2	*
HUCO				
	EVG-HP 1x/2x 15-42W HC	097545	1	
OTHERS				
	Electro Magnetic Ballast			

### Philips CorePro LED PLT

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLT 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLT 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLT 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLT 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLT 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLT 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

# Philips CorePro LED PLT HF/Mains 13.5W 4P GX24Q-3

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLT HF/Mains 13.5W 4P GX24Q-3
				Model number / EOC code: 9290042670 / 872110304981000 9290042671 / 872110304983400
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-P 1 22-42 PL-T/C/L/T5C EI	9137006307	1	
	HF-P 1 26-42 PL-T/C	9137001932	1	
	HF-P 2 22-42 PL-T/C/L/TL5C EII	9137006308	2	
	HF-P 2 26-42 PL-T/C 220-240	9137001950	2	**
OSRAM	QTP-M 1X26-42	A6979600455	1	
	QTP-M 2x26-32	A6979950455 A69799501DG	2	*
	QTP-T/E 1x26-42, 2x26	A72032500DG	1	
	QT-M 2x26-42/220-240 S	A52675500DG	2	*
	QT-M 1x26-42/220-240 S	A37683900DG	1	*
TRIDONIC ATCO	PC 1/2x26-42 TC PRO sr	22176417	1	
	PC 1/2 x 26-42 TC PRO	22176408	1	
	PC 1x26-42 TC TOP	28000075	1	(1)
	PC 2x26-42 TC PRO	22176410	2	
VOSSLOH	ELXc 142.872	188700	1	
	ELXc 142.876	188888	1	
	ELXc 242.837	188643	2	*
	ELXc 242.877	188889	2	*
BAG-HUECO	BCS42.1/26.2LS-01/220-240	10095045	1	
	BCS42.1/26.2QI-01/220-240	10095745	1	
	BCS70.1/42.2Q-01/220-240	10097546	1	
	BCS70.1/42.2Q-01/220-240	10097546	2	
	BCS42.1Q-01/220-240	10097535	1	
	BCS42.1/26.2Q-01/220-240	10097545	1	
TCI	MBQ 142/2	137968/142	1	** (1)
	MBQ 242/2	137962/242	1	** (1)
	MBQ 242/2	137962/242	2	** (1)
HELVAR	EL1/2x18-42TCs	4219001Q09604620 1	1	** (1)
	EL2x32/42TCs	4218001K03102451 9	2	
HUCO	EVG-HP 1x/2x 15-42W HC	097545	1	
OTHERS	Direct mains			
	Electro Magnetic Ballast			

### Philips CorePro LED PLT

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLT 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLT 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLT 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLT 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLT 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLT 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

# Philips CorePro LED PLT HF/Mains 16W 4P GX24Q-4

## Ballast compatibility

### Key

	Ballast is compatible.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions.</i>
*	Ballast is compatible. Light output may differ >10% compared to specifications.	
**	Ballast is compatible. Light output may differ >10% compared to specifications.	
(1)	Ballast Do not use in closed luminaires	
	Ballast is not compatible.	

				CorePro LED PLT HF/Mains 16W 4P GX24Q-4
				Model number / EOC code: 9290042672 / 872110304985800 9290042673 / 872110304987200
				AC (50 Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc	Lamps on ballast	
	HF-P 1 22-42 PL-T/C/L/T5C EII	9137006307	1	
	HF-P 1 26-42 PL-T/C	9137001932	1	
	HF-P 2 22-42 PL-T/C/L/TL5C EII	9137006308	2	
	HF-P 2 26-42 PL-T/C 220-240	9137001950	2	
OSRAM	QTP-M 1X26-42	A6979600455	1	
	QTP-M 2x26-32	A6979950455 A69799501DG	1	*
	QTP-T/E 1x26-42, 2x26	A72032500DG	1	
	QT-M 2x26-42/220-240 S	A5267550355	2	*
	QT-M 1x26-42/220-240 S	A37683900DG	1	*
TRIDONIC ATCO	PC 1/2x26-42 TC PRO sr	22176417	1	
	PC 1/2 x 26-42 TC PRO	22176408	1	
	PC 1x26-42 TC TOP	28000075	1	
	PC 2x26-42 TC PRO	22176410	2	
VOSSLOH	CBC-226142	540426	2	** (1)
	ELXc 142.872	188700	1	
	ELXc 142.876	188888	1	
	ELXc 242.837	188643	2	
	ELXc 242.877	188889	2	*
BAG-HUECO	BCS42.1/26.2LS-01/220-240	10095045	1	
	BCS42.1/26.2QI-01/220-240	10095745	1	
	BCS70.1/42.2Q-01/220-240	10097546	1	
	BCS70.1/42.2Q-01/220-240	10097546	2	
	BCS42.1Q-01/220-240	10097535	1	
	BCS42.1/26.2Q-01/220-240	10097545	1	
TCI	MBQ 142/2	137968/142	1	** (1)
	MBQ 242/2	137962/242	1	** (1)
	MBQ 242/2	137962/242	2	** (1)
HELVAR	EL1/2x18-42TCs	4219001Q09604620 1	1	**
	EL2x32/42TCs	4218001K03102451 9	2	
HUCO	EVG-HP 1x/2x 15-42W HC	097545	1	
OTHERS	Direct mains			
	Electro Magnetic Ballast			

### Philips CorePro LED PLT

**General notes:** Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips CorePro LED PLT 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLT 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed.

Philips CorePro LED PLT 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range.

This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLT 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLT 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on [www.philips.com/ledtube](http://www.philips.com/ledtube).

**Dimming:** Philips CorePro LED PLT 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.

