

E26 6" Trim Series


DESCRIPTION

Shallow full cone reflector trim with self-flange in the 6" trim family for use in recessed downlighting. Compatible for use in Halo and other housings.

Catalog #		Type
Project		
Comments		Date
Prepared by		

SPECIFICATION FEATURES

- Shallow full cone reflector for A19, PAR30, and BR30 lamps
- Torsion spring retention
- Self-flanged trim ring sized to hide gaps caused by construction tolerances.
- Makes installation Air-Tite, with any compatible housing



Dimensions:

A: 4-3/16" [106mm]

H: 4-3/8" [110mm]

OD: 7-3/4" [197mm]

Housings		Max Lamp Compatibility
H7ICT	H7RICT	
H7ICAT	H7RICAT	43W A19, 75W PAR30S, 75W PAR30L, 65W BR30
E7ICAT	E7RICAT	
H7UICAT		75W PAR30S, 75W PAR30L, 85W BR30
H7ICTNB		
H7ICATNB		43W A19, 75W PAR30S, 75W PAR30L, 65W BR30
E7ICATNB		
H27ICAT	E27ICAT	40W A19, 60W PAR30S, 75W PAR30L, 65W BR30
H27RICAT	E27RICAT	
H7T	E7TAT	40W A19, 75W PAR30S, 75W PAR30L, 65W BR30
H7RT	E7RTAT	40W A19, 75W PAR30S, 75W PAR30L, 65W BR30
H7TNB	E7TATNB	40W A19, 75W PAR30S, 75W PAR30L, 65W BR30
H27T	E27TAT	40W A19, 75W PAR30S, 75W PAR30L, 65W BR30
H27RT	E27RTAT	

Compatible with Halogen, Incandescent, LED* or CFL* lamps.



6121WH
White Reflector,
White Trim

6121

6-Inch Shallow Full Cone Reflector, Self-flange



ORDERING INFORMATION

SAMPLE NUMBER: 6121WH

Trim	Finish
6121= 6" Shallow Full Cone Reflector, Self-flange	WH=White reflector and trim

HALO HOUSING COMPATIBILITY

Trim #	Style	H7ICT	H7ICAT	H7RICT	H7RICAT	E7ICAT	E7RICAT	H7UICAT	H7ICTNB
6121	Reflector	•	•	•	•	•	•	—	•
		H7ICATNB	E7ICATNB	H27ICAT	H27RICAT	E27ICAT	E27RICAT		
		•	•	•	•	•	•		
		H7T	H7TCP	H7RT	E7TAT	E7RTAT	H7TNB	E7TATNB	H27T
		•	—	•	•	•	•	•	•
		H27RT	E27TAT	E27RTAT					
		•	•	•					

For use in select other's housings, refer to U.L. classification list at www.cooperlighting.com.

*UL1993 listed LED & CFL equivalent lamps permitted. Consult lamp manufacturer for conditions of use. Cooper Lighting Solutions does not warranty the lamp.



For use in Halo listed housings.



Select trims are classified for use in others housings. See www.cooperlighting.com.