



# Dimming the next step in energy saving

# HF-Regulator Intelligent Touch DALI for TL5/TL-D/PL-L lamps

This intelligent high-frequency electronic dimming ballast utilizes the DALI or Touch and Dim push-button protocol for fluorescent lamps. It meets A1BAT requirements, thereby pre-empting upcoming legislation. With a special command you can retrieve the system's mains power consumption, and with another you can find out which lamp wattage is connected. Combined with controls, additional energy savings can be achieved.

#### **Benefits**

- Extremely low stand-by losses, controlled cut-off for dim levels above 80%, hybrid control dimming (current control at 100% and power control at 1%) combined with MASTER TL5 Eco the most energy-efficient solution
- · HF operation improves light quality and lamp lifetime.
- Compliant with European and Asian norms and suitable for emergency lighting systems

#### **Features**

- HF-R Intelligent recognizes what type of lamp (T5 HE, HO, ECO, TL-D, PL-L) is connected and drives it accordingly
- Programmed start: flicker-free ignition < 1.0 second and striation-free operation, no stroboscopic effects. Preheating the lamp electrodes enables the lamps to be switched on and off without reducing life
- Smart power ensures constant light, independent of mains fluctuations and dimming from 1 to 100%
- Stop circuit is activated within 5 seconds in the event of lamp failure (safety stop),
  and ballast resets automatically after lamp replacement
- Programmable for intelligent functionalities via Philips MultiOne: Corridor mode, Emergency DC dim level, Burn-in time

## HF-Regulator Intelligent Touch DALI for TL5/TL-D/PL-L lamps

#### **Application**


• Indoor, general and task lighting applications in combination with lighting control systems (personal control, daylight linking and/or movement detection)

#### Versions



HF-Ri TD 3 14/24 TL5 E+ 195-240V

#### Dimensional drawing



Approval and application				
Energy Efficiency Index A1 BAT				
Operating and electrical				
Input Frequency	50 to 60 Hz			
Input Voltage	195-240 V			
General information				
Lamp Type	TL5			
Mechanical and housing				
Housing	L 359x30x21			
System characteristics				
Rated Ballast-Lamp Power	28-35-49-54 W			

Product	D1	C1	A1	A2	B1
HF-Ri TD 1 28/35/49/54 TL5	4.1 mm	22.0	360.0	350.0	30.0
E+ 195-240V		mm	mm	mm	mm
HF-Ri TD 2 28/35/49/54 TL5	4.1 mm	22.0	360.0	350.0	30.0
E+ 195-240V		mm	mm	mm	mm

#### General information

## HF-Regulator Intelligent Touch DALI for TL5/TL-D/PL-L lamps

		Number Of			
		Products On MCB	Number Of		
Order Code	Full Product Name	(16A Type B) (Nom)	Lamps	Order Code	Full Produc
502377	HF-Ri TD 1 28/35/49/54 TL5 E+	39	1 piece/unit	502393	HF-Ri TD 2
	195-240V				195-240V

		Number Of	
		Products On MCB	Number Of
Order Code	Full Product Name	(16A Type B) (Nom)	Lamps
502393	HF-Ri TD 2 28/35/49/54 TL5 E+	18	2 piece/unit
	195-240V		

#### System characteristics

						Lamp Power On TL-D
Order Code	Full Product Name	Lamp Power On PL-L	Lamp Power On TL5	Lamp Power On TL5 ECO	Lamp Power On TL-D	ECO
502377	HF-Ri TD 1 28/35/49/54 TL5 E+ 195-240V	51.2 W	29.4/36.4/51.6/54.8 W	26.3/30.2/45.7/50.4 W	52.2 W	42.7 W
502393	HF-Ri TD 2 28/35/49/54 TL5 E+ 195-240V	101.6 W	58.9/73.6/107.2/113.4 W	50.8/66.5/95.6/102.7 W	101.1 W	89.8 W

