

BAS / BAD > BANNER ARMS

> shown here on a straight round pole




BAS(2) / BAD(2) > BANNER ARMS

> shown here on a straight round pole




BABS(2) / BABD(2) > BREAK-AWAY BANNER ARM

> shown here on a straight round pole



BAE > BANNER ARM WITH EYELET

> shown here on a straight round pole



Specifications:

Lumec's Banner Arms BAS / BAD are designed to fit on a round, fluted, square and multi-sided pole, using a central tubing inserted through two opposite 13/8" (35 mm) holes

The aluminum banner arm [11/16" diameter (27 mm)] easily slip-fits into the central tubing and it is secured with the attachment by stainless steel hardware. Completing the installation are two end-of-arm decorative casting.

Consult factory for all banner arm heights and orientations.

Optional Lily Flower end-of-arm casting available (LF option).

Specify width of banner(s) as the xx dimension in the ordering

Order in 1" (25 mm) increments only (ex: BAS11) > Lumec strongly recommends that the banner arm should be at least 8 feet from the ground.

Decorative end-of-arm option

Specifications:

Lumec's Banner Arms BAS(2) / BAD(2) are designed to fit on a round, fluted, square and multi-sided pole, using a central tubing inserted through two opposite 13/8" (35 mm) holes.

The aluminum banner arm [11/16" diameter (27 mm)] easily slip-fits into the central tubing and it is secured with the attachment by stainless steel hardware. Completing the installation are two end-of-arm decorative casting.

Consult factory for all banner arm heights and orientations.

Optional Lily Flower end-of-arm casting available (LF option).

Specify width of banner(s) as the xx dimension in the ordering number.

Order in 1" (25 mm) increments only (ex: BAS(2)11)

> Lumec strongly recommends that the banner arm should be at least 8 feet from the ground.

Decorative end-of-arm option

LF

Specifications:

Lumec's Break-Away Banner Arms BABS(2) / BABD(2) are designed to fit on a round, fluted, square and multi-sided poles, using a central tubing inserted through two opposite 13/8" (35 mm) holes with a cable-secured break-away lower arm.

The aluminum banner arm [11/16" diameter (27 mm)] easily slip-fits into the central tubing and it is secured with the attachment by stainless steel hardware. Completing the installation are two end-of-arm decorative casting.

Consult factory for all banner arm heights and orientations.

Optional Lily Flower end-of-arm casting available (LF option).

Specify width of banner(s) as the xx dimension in the ordering number.

Order in 1" (25 mm) increments only (ex: BABS(2)11)

> Lumec strongly recommends that the banner arm should be at least 8 feet from the ground.

Decorative end-of-arm option

LF

Specifications:

Lumec's Banner Arms BAE is designed to fits on a round, fluted, square and multisided poles, using a banner arm fitter inserted through two opposite 13/8" (35 mm) holes completed with eyelet below banner arm installed on pole.

The aluminum banner arm [11/16" diameter (27 mm)] easily slip-fits into the central tubing and it is secured with the attachment by stainless steel hardware. Completing the installation are two end-of-arm decorative casting.

Consult factory for all banner arm heights and orientations.

Optional Lily Flower end-of-arm casting available (LF option).

Specify width of banner(s) as the xx dimension in the ordering number.

Order in 1" (25 mm) increments only (ex: BAS11)

> Lumec strongly recommends that the banner arm should be at least 8 feet from the ground.

Decorative end-of-arm option



LF