



PrimaVision Power for CDM

HID-PV C 150 /S CDM 220-240V 50/60Hz

PrimaVision Power gear is designed for optimal performance of 100 and 150 W CDM lamps – ideal where high-intensity light is key.

Product data


Operating and Electrical	
Input Voltage	220 to 240 V
Line Frequency	50 to 60 Hz
Input Frequency	50 to 60 Hz
Earth Leakage Current (Max)	0.35 mA
Inrush Current Width	.50 ms
Inrush Current Peak (Max)	50 A
Number of Products on MCB (16A Type B)	6
(Nom)	
Wiring	
Cable Length From Device to Lamp	2.0 m
Connector Type	Insert
Temperature	
Ambient temperature range	-20 °C to 60 °C
T-Case Lifetime (Nom)	75 ℃
T-Case Maximum (Max)	85 ℃

Mechanical and Housing				
Housing	/S			
Approval and Application				
Approval Marks	F-Marking CE marking VDE certificate VDE-			
	EMV certificate CB Certificate			
Product Data				
Order product name	HID-PV C 150 /S CDM 220-240V 50/60Hz			
Full product name	HID-PV C 150 /S CDM 220-240V 50/60Hz			
Full product code	871150091052330			
Order code	913700614066			
Material Nr. (12NC)	913700614066			
Numerator - Quantity Per Pack	1			
EAN/UPC - Product/Case	8711500910523			
Numerator - Packs per outer box	12			
EAN/UPC - Case	8711500910530			

Datasheet, 2023, April 16 data subject to change

PrimaVision Power for CDM

Dimensional drawing



Product	D1	C1	A1	A2	B1	B2
HID-PV C 150 /S CDM	4.8 mm	32.0 mm	135.0 mm	123.5 mm	75.0 mm	63.5 mm
220-240V 50/60Hz						



© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.