



Xitanium LED Driver Outdoor Dimmable (US)

Xitanium 150W 120-277V 1.05A 0-10V

Xitanium Outdoor LED Drivers are available in wattages from 40W to 150W for hard-wire integration into outdoor luminaires for the most rugged applications. These drivers operate to specification under wide temperature and electrical ranges to ensure reliability. 1-10V dimming enables luminaires to be easily connected to a wide variety of sensors and control systems to facilitate dimming, thus maximizing energy savings.

Product data

| General Information | | | | |
|-------------------------------------|-------------|--|--|--|
| Lighting Technology | LED | | | |
| | | | | |
| Operating and Electrical | | | | |
| Line Frequency | 50 to 60 Hz | | | |
| Input Frequency | 50 to 60 Hz | | | |
| Total Harmonic Distortion IEC (Max) | 20 % | | | |
| Power Consumption | 167 W | | | |
| Output Current (Nom) | 1050 mA | | | |
| Output Current Tolerance (Max) | 5 % | | | |
| Output Current Tolerance (Min) | -5 % | | | |
| Output Power (Nom) | 150 W | | | |
| | | | | |
| Wiring | | | | |
| Primary Fusing | Fused | | | |
| | | | | |

| Input Wire Gauge | 18 | | | | |
|--------------------------|-------------------------|--|--|--|--|
| | | | | | |
| Temperature | | | | | |
| T-Case Maximum (Max) | 80 ℃ | | | | |
| | | | | | |
| Controls and Dimming | | | | | |
| Control Interface | 0-10V | | | | |
| Dimming Range | 100-10 % | | | | |
| | | | | | |
| Approval and Application | | | | | |
| Overheating Protection | Protected | | | | |
| Short Circuit Protection | Self-limited | | | | |
| Over Power Protection | Protected | | | | |
| Open Circuit Protection | Protected | | | | |
| EMI Standard | FCC 47 Part 15; Class A | | | | |
| Environmental Standard | UL Damp & Dry | | | | |


Datasheet, 2023, December 1 data subject to change

Xitanium LED Driver Outdoor Dimmable (US)

| Approval Marks | RoHS compliance UL certificate CSA certificate |
|---------------------|--|
| | |
| Product Data | |
| Order product name | Xitanium 150W 120-277V 1.05A 0-10V |
| Full product name | Xitanium 150W 120-277V 1.05A 0-10V |
| Order code | 929000722913 |
| Material Nr. (12NC) | 929000722913 |

| Numerator - Quantity Per Pack | 1 | |
|---------------------------------|----------------|--|
| EAN/UPC - Product/Case | 781087135723 | |
| Numerator - Packs per outer box | 10 | |
| EAN/UPC - Case | 50781087135735 | |

Dimensional drawing



| Product | D1 | B2 | C1 | C2 | A1 | A2 | B1 |
|----------------|--------|---------|---------|---------|----------|----------|---------|
| Xitanium 150W | 4.8 mm | 42.9 mm | 39.7 mm | 37.7 mm | 240.5 mm | 241.5 mm | 59.1 mm |
| 120-277V 1.05A | | | | | | | |
| 0-10V | | | | | | | |

