PHILIPS Lighting



Xitanium Linear Isolated LED drivers Adjustable Current

Xitanium 75W 0.7-2.0A 54V 230V

Xitanium LED drivers are designed to operate LED solutions for general lighting applications such as linear lighting, as well as downlighting and spot/accent lighting. High reliability underpinned by 5-year warranty, enhanced by specific features that protect the connected LED module, e.g. hot wiring, reduced ripple current and thermal derating. Most drivers feature central DC operation. In the coming years LEDs will continue to increase in efficiency, creating generation and complexity challenges for OEMs. With Xitanium LED drivers, flexibility in luminaire design is assured thanks to an adjustable output current. Application-oriented operating windows offer the flexibility required to provide the stable lumen output and light quality levels that lighting specifiers and architects demand. And the adjustable output current also enables operation of various LED PCB solutions from different manufacturers.

Product data

General Information		
Lighting Technology	LED	
Operating and Electrical		
Line Frequency	50 to 60 Hz	
Input Frequency	50 to 60 Hz	
Mains voltage operation (DC)	168-275 V	
Total Harmonic Distortion IEC (Max)	20 %	
Power Consumption	75 W	
12V Output	No	

Output Current Ripple (Max)	4 %
Maximum Efficiency at Full Load	88 %
Output Current (Max)	2000 mA
Output Current (Nom)	1350 mA
Output Current Tolerance (Max)	5 %
Mains voltage performance (DC)	186-250 V
Earth Leakage Current (Max)	0.3 mA
Open Circuit Voltage (DC) (Max)	60 V
Input Current (Nom)	420 mA
Inrush Current Peak (Max)	21 A

Xitanium Linear Isolated LED drivers Adjustable Current

Output Power (Max)	75 W
Output Power (Nom)	48 W
Default output current	700-2000 mA
Inrush Current Width to 50% of Peak	220 µs
Energy Metering	No
Constant Current (CC)	True
Constant Voltage (CV)	False
Diagnostics	False
Number of Products on MCB (16A Type B)	24
(Max)	

Wiring	
Connector Type Input Terminals	Wago 744
Hot Wiring	No
Connector Type Output Terminals	Wago 744
Output Wire Cross Section (Max)	1.5 mm²
Output Wire Cross Section (Min)	0.5 mm²
Cable Length From Device to Lamp	4 m
Input wire strip length	8 mm to 9 mm mm
Input Wire Cross Section (Max)	1.5 mm²
Input Wire Cross Section (Min)	0.5 mm²
Output wire strip length	8 mm to 9 mm mm
Temperature	
Ambient temperature range	-20 °C to 50 °C
T-Case Lifetime (Nom)	75 ℃
T-Case Maximum (Max)	75 ℃
Maximum case temperature (in case of	110 °C

None

Mechanical and Housing	
Housing	L360
Approval and Application	
Ingress protection code	IP20 [Finger-protected]
Surge Protection (Common/Differential)	EN61547 (L-L 1kV, L-G 2kV) kV
Relative Humidity (Operation) (Max)	90 %
Isolation Classification	Class I and Class II
Short Circuit Protection	Protected
Over Power Protection	Protected
Open Circuit Protection	Protected
Approval Marks	CE marking ENEC certificate CCC
	certificate SELV
Corridor Mode	False
Output Current Set Options	LEDset
Product Data	
Order product name	Xitanium 75W 0.7-2.0A 54V 230V
Full product name	Xitanium 75W 0.7-2.0A 54V 230V
Full product code	871869646889000
Order code	929000958806
Material Nr. (12NC)	929000958806
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	8718696468890
Numerator - Packs per outer box	24
EAN/UPC - Case	8718696468906

Dimensional drawing

Controls and Dimming Control Interface

failure)



Product	A1	A2	B1	C1	D1
Xitanium 75W 0.7-2.0A 54V 230V	360 mm	350 mm	30 mm	21 mm	4.1 mm

Xitanium Linear Isolated LED drivers Adjustable Current



© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

www.lighting.philips.com 2023, September 19 - data subject to change