PHILIPS Lighting



Essential LEDspot PAR

Essential LED 10-80W PAR38 827 25D

Essential LED PAR is an affordable LED spot lamp that is designed as a retrofit replacement for halogen spots PAR lamps. It provides a natural lighting effect as well as instant energy savings – an environment-friendly solution. The Philips Essential LED family is designed for spot and general lighting applications in the hospitality and retail segments.

Product data

General Information	
Cap-Base	E27 [E27]
Nominal lifetime	15,000 hour(s)
Switching Cycle	25,000
Lighting Technology	LED
EU RoHS compliant	Yes
Light Technical	
Color Code	827 [CCT of 2700K]
Beam Angle (Nom)	25 degree(s)
Luminous Flux	900 lm
Luminous Intensity (Nom)	1,800 cd
Color Designation	Warm White (WW)
Correlated Color Temperature (Nom)	2700 K
Luminous Efficacy (rated) (Nom)	90.00 lm/W
Color Consistency	<6
Color rendering index (CRI)	80
LLMF At End Of Nominal Lifetime (Nom)	70 %

Operating and Electrical	
Line Frequency	50 to 60 Hz
Input Frequency	50 to 60 Hz
Power Consumption	10 W
Lamp Current (Nom)	44 mA
Wattage Equivalent	80 W
Starting Time (Nom)	0.5 s
Warm-up time to 60% light	0.5 s
Power Factor (Fraction)	0.9
Voltage (Nom)	220-240 V
Temperature	
T-Case Maximum (Nom)	80 °C
Controls and Dimming	
Dimmable	No
Mechanical and Housing	
Bulb Shape	PAR38 [PAR 4.75 inch/121mm]

Essential LEDspot PAR

Approval and Application	
Suitable For Accent Lighting	Yes
Energy Consumption kWh/1000 h	10 kWh
Product Data	
Order product name	Essential LED 10-80W PAR38 827 25D

Essential LED 10-80W PAR38 827 25D


871869672867300

Order code	72867300
Material Nr. (12NC)	929001322708
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	8718696728673
Numerator - Packs per outer box	6
EAN/UPC - Case	8718696728680

Dimensional drawing


Full product name

Full product code




Product	D	с
Essential LED 10-80W PAR38 827 25D	122 mm	134 mm

Photometric data



Spectral Power Distribution Colour - Essential LED 10-80W PAR38 827 25D



Light Distribution Diagram - Essential LED 10-80W PAR38 827 25D


	1 x 9290013227 27088 9W
	1 a 900 im
The input dependence of the in	

Philos Listene B.V.

Accent Lighting Spots - Essential LED 10-80W PAR38 827 25D

Essential LEDspot PAR

Lifetime



Life Expectancy Diagram - Essential LED 10-80W PAR38 827 25D

Lumen Maintenance Diagram - Essential LED 10-80W PAR38 827 25D



© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

www.lighting.philips.com 2023, July 26 - data subject to change