PHILIPS Lighting



Emergency lighting kit

EM300V ELP3 kit HV 6.4V 2000mAh LFP

Emergency lighting kit, Accessory

Philips Emergency Lighting Kits are designed to convert general lighting luminaires into emergency luminaires — quickly, easily and on site. A choice of two kits are available to suit different types of luminaires: the built-in kit is designed to use with linear luminaires, like waterproof and batten luminaires; the independent kit is perfect for recessed luminaires, like panels and downlights. Each kit consists of an Emergency LED driver and a LifePO4 (lithium iron phosphate) battery. In case of an emergency, luminaires will switch to battery mode to provide sufficient emergency indoor lighting for three hours. Quick and easy to install, the emergency lighting module in the kits eliminates any complexity thanks to an LED indicator and a selftest (ELP) or manual test (ELB) option for added peace of mind that the emergency lighting mode is operating correctly. The battery compartment is also easy to open for fast and easy battery replacements. Philips Emergency Lighting Kits can be bought as an addition to many of our luminaires, so there's no need to decide whether you need emergency lighting upfront or not. Convertible emergency lighting is possible even after your luminaires have been installed. Simply order the right kit for your choice of luminaires and when you need to switch on emergency lighting capabilities, you're good to go.

Product data

| General Information | | |
|--------------------------|-----------------|--|
| Value ladder | Value | |
| | | |
| Operating and Electrical | | |
| Input Voltage | 220 to 240 V | |
| Line Frequency | 50 to 60 Hz | |
| Protection class IEC | Safety class II | |


| Mechanical and Housing | |
|-------------------------------------|-------------------------|
| Overall length | 220 mm |
| Overall width | 42 mm |
| Overall height | 28 mm |
| Overall diameter | 0 mm |
| Dimensions (height x width x depth) | 28 x 42 x 220 mm |
| Material | Polycarbonate |
| Ingress protection code | IP20 [Finger-protected] |

Emergency lighting kit

| Mech. impact protection code | - |
|------------------------------|-------------------------------------|
| Accessory colour | White |
| Net Weight (Piece) | 0.240 kg |
| | |
| Approval and Application | |
| CE mark | Yes |
| EU RoHS compliant | Yes |
| | |
| Product Data | |
| Order product name | EM300V ELP3 kit HV 6.4V 2000mAh LFP |
| Full product name | EM300V ELP3 kit HV 6.4V 2000mAh LFP |
| | |

| Full EOC | 871869979821500 |
|---------------------------------|-----------------|
| Local code description | ECO-E3/ST-NC/BT |
| Order code | 79821500 |
| Material no. (12 NC) | 912401483460 |
| Local order code | ECO-E3/ST-NC/BT |
| Numerator – quantity per pack | 1 |
| EAN/UPC — Product/Case | 8718699798215 |
| Numerator – packs per outer box | 1 |
| EAN/UPC - Case | 8718699798215 |
| | |

Dimensional drawing





© 2023 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

www.lighting.philips.com 2023, November 29 - data subject to change