

[illegible][illegible]

Applicable Philips Part Numbers											
9290022399 (552398)											
 AR111											
Wall Box											
Lutron								Leviton			
CTELV-303P	DVELV-300P	MAELV-600	MALV-600	NLV-600 2	NTLV-600	RRD-6NA 2	SLV-600P	6613	6615	IPE041	IPM10
			NR	NR	NR		NR	/			NR
			NR	NR	NR		NR	/			NR
	NR		NR	NR	NR	NR	NR	/			NR
			NR	NR	NR		NR	/			NR
			NR	NR	NR	NR	NR	/	NR		NR
NR		NR	NR	NR	NR	NR	NR	/	NR	NR	NR
		NR	NR	NR	NR	NR	NR	/	NR	NR	NR
		NR	NR	NR	NR	NR	NR	/	NR	NR	NR
		NR	NR	NR	NR	NR	NR	/	NR	NR	NR
		NR	NR	NR	NR	NR	NR	/	NR	NR	NR
			NR	NR	NR		NR	/	NR		NR
/	/	/	/	/	/	/	/	/	/	/	/
NR	NR	NR			NR				NR	NR	
NO DIMMER / Number of Lamps											
1	2	3	4	5	6						
/											
/											
/											
/											

† This transformer should have less than Three(3) units on a single branch of mains.

KEY (May exhibit one or several of the described parameters within the group)

	No Flickering above 10%.
	No Flickering above 30%.
NR	Use of this dimmer/lamp combination not recommended.
/	Not Tested.

Note:

- (1) Transformer load is limited to 20% of the halogen rating unless other value recommended by the transformer manufacturer.
- (2) Number of Lamps = (Transformer Watts x 20%) / (Lamp Watts).
- (3) Transformers designed for LED loads are not subjected to this derating rule.
- (4) 1 Lamp tested
- (5) Absence of a transformer from this chart does not imply incompatibility.

** Min 2 Lamps *** Min 3 Lamps

		Applicable Philips Part Numbers												
		 9290030808 (573584) 9290030810 (573600) 9290030811 (573618) 9290030814 (573642)												
		ExpertColor												
Transformer Company	Model No.	Wall Box												
		Lutron							Leviton			Panel Lutron		
		CTELV-303P	DVELV-300P	MAELV-600	MALV-600	NTLV-600	RPD-6NA 2	SLV-600P	6615	IPE04 1	DSM10	GP (Harrier) Card with PHPM-WMX -120 2	HW/LP-RPM -4U-120 2	LCP-1Q1A-120FT with RPM-4A-120 2
GE/LighTech	LET-60				NR	NR		NR			NR			
GE/LighTech	LET-60-LW	NR	NR		NR	NR		NR			NR			
GE/LighTech	LET-75				NR	NR		NR		NR	NR			
Hatch	RS12-150	NR		**	NR	NR		NR			NR			
Hatch	RS12-15M-LED†				NR	NR		NR	NR	NR	NR	NR	NR	NR
Hatch	RS12-60M	NR			NR	NR		NR		NR	NR			
Hatch	RS12-60M-LED†				NR	NR		NR	NR		NR	NR	NR	NR
Hatch	RS12-80M				NR	NR		NR			NR	NR	**	**
Keystone	KTET-150-1-SCP-DIM	NR			NR	NR		NR			NR	**	**	**
Keystone	KTET-60-1-SCP-DIM-AL	NR			NR	NR		NR			NR			
Keystone	KTET-60-1-WC-F	NR		NR	NR	NR		NR			NR			
Keystone	KTET-75-1-SCP-DIM-HV-AL	NR			NR	NR		NR	NR		NR			
Philips	71A9743	NR	NR	NR	NR				NR	NR				
Transformer Company	Model No.	NO DIMMER / Number of Lamps												
		1			2			3			4			
GE/LighTech	LET-60													
GE/LighTech	LET-60-LW													
GE/LighTech	LET-75													
GE/LighTech	LET-75-277-R		/											
Hatch	RS12-150													
Hatch	RS12-15M-LED†													
Hatch	RS12-60M													
Hatch	RS12-60M-LED†											Flicker		
Hatch	RS12-80-277M													
Hatch	RS12-80M													
Keystone	KTET-150-1-SCP-DIM													
Keystone	KTET-60-1-SCP-DIM-AL													
Keystone	KTET-60-1-WC-F													
Keystone	KTET-75-1-SCP-DIM-HV-AL													
Keystone	KTET-75-2-SCP-RJS													
Luminiz	TRP60													
Philips	71A9743													
Philips	71A9833		/											
WAC Lighting	EN-1260-R2													

1 Audible noise may be observed when used with this dimmer, depending on the application.

2 This dimmer has low end trim adjustment that may be used for optimal performance.

† This transformer should have less than Three(3) units on a single branch of mains.

KEY (May exhibit one or several of the described parameters within the group)

	No Flickering above 10%.
	No Flickering above 30%.
NR	Use of this dimmer/lamp combination not recommended.
/	Not Tested.

Note:

(1) Transformer load is limited to 20% of the halogen rating unless other value recommended by the transformer manufacturer.

(2) Number of Lamps = (Transformer Watts x 20%)/ (Lamp Watts).

(3) Transformers designed for LED loads are not subjected to this derating rule.

(4) 1 Lamp tested

(5) Absence of a transformer from this chart does not imply incompatibility.

** Min 2 Lamps *** Min 3 Lamps

		Applicable Philips Part Numbers												
		 9290030803 (573535) 9290030805 (573550) 9290030806 (573568)												
		ExpertColor												
Transformer Company	Model No.	Wall Box												
		Lutron							Leviton			Panel Lutron		
		DVELV-300P	MAELV-600	MALV-600	NTLV-600	RPD-6NA 2	SLV-600P	6615	IPE04 1	DSM10	GP (Harrier) Card with PHPM-WMX -120 2	HW/LP-RPM -4U-120 2	LCP-1Q1A-120FT with RPM-4A-120 2	
				NR	NR		NR				NR			
NR	NR			NR	NR		NR				NR			
				NR	NR		NR				NR			
NR				NR	NR		NR				NR			
				NR	NR		NR	NR	NR	NR	NR	NR	NR	NR
NR				NR	NR		NR				NR			
				NR	NR		NR	NR			NR		NR	NR
				NR	NR		NR				NR	*		
NR	NR	**	NR	NR	NR	NR	NR		**	NR	NR	**	**	**
NR				NR	NR		NR				NR			
NR			NR	NR	NR		NR				NR			
NR				NR	NR		NR	NR			NR			
NR	NR	NR	NR	NR			NR		NR	NR				
Transformer Company	Model No.	NO DIMMER / Number of Lamps												
		1			2			3			4			
/														
/														

		Applicable Philips Part Numbers											
		 9290030762 (573865) 9290030763 (573873) 9290030764 (573881) 9290030765 (573899)											
Transformer Company	Model No.	Wall Box						Panel					
		Lutron						Lutron					
		CTELV-303P	DVELV-300P	MAELV-600	MALV-600	NTLV-600	RPD-6NA 2	SLV-600P	6615	IPE04 1	DSM10	GP (Harrier) Card with PHPM-WMX -120 2	LCP-1QIA-120FT with RPM-4A-120 2
GE/LighTech	LET-60				NR	NR		NR			NR		
GE/LighTech	LET-60-LW	NR	NR		NR	NR		NR		NR	NR		
GE/LighTech	LET-75				NR	NR		NR		NR	NR		
Hatch	RS12-150	NR		**	NR	NR		NR	**		NR		
Hatch	RS12-15M-LED†				NR	NR		NR	NR	NR	NR	NR	NR
Hatch	RS12-60M	NR			NR	NR		NR		NR	NR		
Hatch	RS12-60M-LED†				NR	NR	NR	NR	NR	NR	NR	NR	NR
Hatch	RS12-80M				NR	NR	NR	NR		NR		**	**
Keystone	KTET-150-1-SCP-DIM	NR			NR	NR		NR	**		NR		
Keystone	KTET-60-1-SCP-DIM-AL	NR			NR	NR		NR			NR		
Keystone	KTET-60-1-WC-F	NR		NR	NR	NR		NR			NR		
Keystone	KTET-75-1-SCP-DIM-HV-AL	NR			NR	NR		NR	NR		NR		
Philips	71A9743	NR	NR	NR	NR			NR		NR			
Transformer Company	Model No.	NO DIMMER / Number of Lamps											
		1	2	3	4								
GE/LighTech	LET-60												
GE/LighTech	LET-60-LW												
GE/LighTech	LET-75												
GE/LighTech	LET-75-277-R	/											
Hatch	RS12-150												
Hatch	RS12-15M-LED†		Flicker										
Hatch	RS12-60M												
Hatch	RS12-60M-LED†									Flicker			
Hatch	RS12-80-277M												
Hatch	RS12-80M												
Keystone	KTET-150-1-SCP-DIM												
Keystone	KTET-60-1-SCP-DIM-AL												
Keystone	KTET-60-1-WC-F												
Keystone	KTET-75-1-SCP-DIM-HV-AL												
Keystone	KTET-75-2-SCP-RJS												
Luminiz	TRP60												
Philips	71A9743												
Philips	71A9833	/											
WAC Lighting	EN-1260-R2												

1 Audible noise may be observed when used with this dimmer, depending on the application.

2 This dimmer has low end trim adjustment that may be used for optimal performance.

† This transformer should have less than Three(3) units on a single branch of mains.

KEY (May exhibit one or several of the described parameters within the group)

	No Flickering above 10%.
	No Flickering above 30%.
NR	Use of this dimmer/lamp combination not recommended.
/	Not Tested.

Note:

(1) Transformer load is limited to 20% of the halogen rating unless other value recommended by the transformer manufacturer.

(2) Number of Lamps = (Transformer Watts x 20%) / (Lamp Watts).

(3) Transformers designed for LED loads are not subjected to this derating rule.

(4) 1 Lamp tested

(5) Absence of a transformer from this chart does not imply incompatibility.

** Min 2 Lamps *** Min 3 Lamps

		Applicable Philips Part Numbers											
		 9290030725 (573907) 9290030726 (573915) 9290030727 (573931) 9290030728 (573949) 9290030729 (573955)											
Transformer Company	Model No.	Wall Box						Panel					
		Lutron						Lutron					
		DVELV-300P	MAELV-600	MALV-600	NTLV-600	RPD-6NA 2	SLV-600P	6615	IPE04 1	DSM10	GP (Harrier) Card with PHPM-WMX -120 2	HW/LP-RPM -4U-120 2	LCP-1QIA-120FT with RPM-4A-120 2
NR				NR	NR		NR		NR	NR			
NR	NR			NR	NR		NR			NR			
**				NR	NR		NR		NR	NR			
NR			**	NR	NR		NR			NR			
				NR	NR		NR	NR	NR	NR	NR	NR	NR
NR				NR	NR		NR		NR	NR			
				NR	NR		NR	NR		NR		NR	NR
				NR	NR		NR			NR	*		
NR				NR	NR		NR			NR			
NR				NR	NR		NR			NR			
NR		NR		NR	NR		NR			NR			
NR			NR	NR	NR		NR	NR		NR			
NR	NR	NR	NR	NR			NR		NR	NR			
Transformer Company	Model No.	NO DIMMER / Number of Lamps											
		1	2	3	4								
/													
/													

		Applicable Philips Part Numbers												
		 9290030871 (574400) 9290030872 (574418) Warm Glow												
Transformer Company	Model No.	Wall Box									Panel			
		Lutron						Leviton			Lutron			
		CTELV-303P	DVELV-300P	MAELV-600	MALV-600	NTLV-600	RRD-6NA 2	SLV-600P	6615	IPE04 1	DSM10	GP (Harrier) Card with PHPM-WMX -120 2	HW/LP-RPM -4U-120 2	LCP-1Q1A-120FT with RPM-4A- 120 2
GE/LighTech	LET-60			NR	NR	NR		NR			NR	**		
GE/LighTech	LET-60-LW				NR	NR		NR			NR			
GE/LighTech	LET-75				NR	NR		NR			NR			
Hatch	RS12-150				NR	NR		NR			NR			
Hatch	RS12-15M-LED†				NR	NR		NR	NR		NR	NR	NR	NR
Hatch	RS12-60M				NR	NR		NR			NR			
Hatch	RS12-60M-LED†				NR	NR		NR			NR		NR	NR
Hatch	RS12-80M				NR	NR		NR			NR		NR	NR
Keystone	KTET-150-1-SCP-DIM				NR	NR		NR			NR	NR		
Keystone	KTET-60-1-SCP-DIM-AL				NR	NR		NR			NR			
Keystone	KTET-60-1-WC-F				NR	NR		NR			NR			
Keystone	KTET-75-1-SCP-DIM-HV-AL				NR	NR		NR						
Philips	71A9743	NR	NR	NR	NR		NR		NR	NR				
Transformer Company	Model No.	NO DIMMER / Number of Lamps												
		1			2			3			4			
GE/LighTech	LET-60													
GE/LighTech	LET-60-LW													
GE/LighTech	LET-75													
GE/LighTech	LET-75-277-R	Flicker			Flicker									
Hatch	RS12-150													
Hatch	RS12-15M-LED†													
Hatch	RS12-60M													
Hatch	RS12-60M-LED†													
Hatch	RS12-80-277M	Flicker			Flicker									
Hatch	RS12-80M													
Keystone	KTET-150-1-SCP-DIM													
Keystone	KTET-60-1-SCP-DIM-AL													
Keystone	KTET-60-1-WC-F													
Keystone	KTET-75-1-SCP-DIM-HV-AL													
Keystone	KTET-75-2-SCP-RJS	Flicker			Flicker									
Luminiz	TRP60													
Philips	71A9743													
Philips	71A9833	/												
WAC Lighting	EN-1260-R2													

1 Audible noise may be observed when used with this dimmer, depending on the application.

2 This dimmer has low end trim adjustment that may be used for optimal performance.

† This transformer should have less than Three(3) units on a single branch of mains.

KEY (May exhibit one or several of the described parameters within the group)

	No Flickering above 10%.
	No Flickering above 30%.
NR	Use of this dimmer/lamp combination not recommended.
/	Not Tested.

Note:

(1) Transformer load is limited to 20% of the halogen rating unless other value recommended by the transformer manufacturer.

(2) Number of Lamps = (Transformer Watts x 20%)/ (Lamp Watts).

(3) Transformers designed for LED loads are not subjected to this derating rule.

(4) 1 Lamp tested

(5) Absence of a transformer from this chart does not imply incompatibility.

** Min 2 Lamps *** Min 3 Lamps



© 2025 Signify Holding. All rights reserved. The information provided herein is subject to change, without notice. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify.

08/2025 philips.com/lighting

Signify North America Corporation
200 Franklin Square Drive,
Somerset, NJ 08873
Telephone 855-486-2216

Signify Canada Ltd.
281 Hillmount Road,
Markham, ON, Canada L6C 2S3
Telephone 800-668-9008

Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.
All other trademarks are owned by Signify Holding or their respective owners.