



The affordable LED solution

Essential LEDspot PAR

Essential LED PAR is an affordable LED spot lamp that is designed as a retrofit replacement for halogen spots PAR lamps. It provides a natural lighting effect as well as instant energy savings – an environment-friendly solution. The Philips Essential LED family is designed for spot and general lighting applications in the hospitality and retail segments.

Benefits

- Reduced operational cost thanks to energy savings of up to 80%
- Lower maintenance cost thanks to more than five times longer lifetime than conventional halogen spot lamps
- Easy retrofit, upgrading the existing luminaire to LED technology
- Low initial investment

Features

- Lower energy consumption compared to halogen spot PAR lamp
- Retrofit replacement of halogen spot lamps with existing transformers
- Lifetime up to 15,000 hours
- Non-dimmable

Application

- Hospitality (restaurants, hotels, coffee bars)
- Retail


Essential LEDspot PAR

Versions



LEDspots PAR38 E26 1

Dimensional drawing




Product	D	C
Essential LED 14-120W PAR38 827 25D	125 mm	133 mm
LED 14-120W PAR38 827 25D	125 mm	133 mm

Essential LEDspot PAR

General Information	
Cap-Base	E27
Switching Cycle	50,000
Nominal lifetime	15,000 hour(s)
Light Technical	
Beam Angle (Nom)	25 degree(s)
Correlated Color Temperature (Nom)	2700 K
Color rendering index (CRI)	80
Color Code	827
LLMF At End Of Nominal Lifetime (Nom)	70 %
Luminous Flux	1,200 lm
Luminous Intensity (Nom)	5,000 cd
Operating and Electrical	
Input Frequency	50 to 60 Hz
Line Frequency	50 to 60 Hz
Power Consumption	14 W
Starting Time (Nom)	0.5 s
Wattage Equivalent	120 W
Temperature	
T-Case Maximum (Nom)	75 °C
Controls and Dimming	
Dimmable	No
Mechanical and Housing	
Bulb Shape	PAR38
Approval and Application	
Energy Consumption kWh/1000 h	14 kWh


General Information

Order Code	Full Product Name	Rated Lifetime (Hours)
929002339107	LED 14-120W PAR38 827 25D	15,000 hour(s)
929002339108	Essential LED 14-120W PAR38 827 25D	-




Essential LEDspot PAR

Accent Diagrams



Accent Diagram - LED 14-120W PAR38 827 25D

Beam Diagrams



Beam diagram - LED 14-120W PAR38 827 25D

