PHILIPS Lighting



3 hours compliant exit sign emergency light

Emergency Light LED Exit Sign

Safety is important for building owners, and therefore having proper emergency lighting in place is a major concern for them. The Emergency exit sign offers an easy solution for stand-alone emergency lighting, with maintained mode and various installation methods which are suitable for different applications. The lithium battery (LiFePO4) has many advantages over nickel-based products, as it has a longer lifetime, better discharge behaviors, is produced in a more welfare friendly way and can be recycled.

Benefits

- Welfare friendly solution versus nickel-based products as the battery can be recycled.
- Lithium based battery type provides longer lifetime, low self-discharge and high temperature tolerance.

Features

- \cdot 3 hours battery duration when full charged
- \cdot Self-test function
- \cdot LFP is designed environmental friendly
- Maintained mode
- Safety & reliable

Application

- Airports
- Offices
- Retail

Specifications

Mounting type

Recessed/wall/ceiling/flag/suspended

Emergency Light LED Exit Sign

Operating Temperature +0 to +45 °C		Ingress protection	IP20
range		Light source	No
Light Source	LED	replaceable	
Mains Voltage	220-240V/50-60Hz	Driver replaceable	No
Mechanical Accessori	es Flag ins. kit	Overall height	42
	Recessed ins. kit	Overall length	313
	Suspended ins. kit	Overall width	212
	legend with directions	UGR	22
Dimming	PSU	Installation	Ceiling
Emergency lighting	Emergency lighting Pro 3hrs		Wall
Material	PC		Flag
Main color of the	RAL 9003		Recessed
luminaire			Suspended
Protection Class	class II	Warranty	1 year
IEC61140			

Versions








Emergency light LED exit sign

Emergency light LED exit sign

Emergency light LED exit sign

Dimensional drawing







Emergency Light LED Exit Sign

Dimensional drawing



Product details



Emergency light LED exit sign



Emergency light LED exit sign



Emergency light LED exit sign



© 2024 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2024, November 27 - data subject to change